

July 31, 2018

**HB1022A Triac/Forward Phase-cut dimmers**

Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	minimum dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	8	3-Way only works with a 3-Way switch	2%
			TGCL-153P							
		Diva C.L	DVCL-153P							
		Skylark C.L	SCL-153P							
		Skylark Contour C.L	CTCL-153P							
		Lumea C.L	LGCL-153P			slide with ON/OFF button				
		Maestro C.L	MACL-153M	Single-pole/3-way/multi-location	150	Digital	2014	8	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	3%
			MSCL-VP153M	Single-pole/3-way/multi-location	150	Digital/Vacancy Sensor	T2	8	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	3%
			MSCL-OP153M	Single-pole/3-way/multi-location		Digital/Occupancy Sensor				
			MRF2-6CL	Single-pole/3-way/multi-location	150	Digital and Wireless	M6	8	3-Way or multi-location only works with companion MA-R (not a dimmer)	3%
	Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	13		3%	
	Grafik T	GT-150	Single-pole/3-way/multi-location	150	Digital	T6	8	3-Way or multi-location only works with companion GT-AD (not a dimmer)	3%	
RF C.L	Grafik T RF	GTJ 150	M6			3%				
	Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless,	SD11	8	Multi-location only works with Pico wireless remote PJ2, amazon alexa, Google Assistant, Apple HomeKit, Apple Watch	3%
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	16	3-Way only works with a 3-Way switch	16%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	8	3-Way only works with a 3-Way switch	2%
		Sureslide	6672-1L	single	150	slide to off	NA	8		7%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	8	3-Way only works with a 3-Way switch	3%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	16	3-Way only works with remote RE00R Requires neutral wire connection	3%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	25	3-Way only works with remote DDOOR-DL Requires neutral wire connection	3%

