

Step-By-Step Quick Start Guide To Using Your Generator

1 Remove Generator From Package

2 Add Oil

Oil Type: SAE10W-30 Oil (Must add BEFORE first use)
Oil Capacity: 12.0 fluid oz
Because this generator includes Low Oil Shut Off, the generator will not start with low oil. Start out with 12.0 oz, then **fill until almost overflowing.**)

3 Add Fuel

Unleaded gasoline only octane rating of 87 or higher
Maximum Capacity: 1.2 Gallon fuel tank

4 Start The Generator

- Use the generator OUTDOORS in a WELL VENTILATED AREA.
- DO NOT CONNECT electrical devices until AFTER the generator is started.
- Turn Engine Switch to ON
- Turn FUEL PETCOCK to ON (Figure A)
- Adjust the CHOKE to CLOSED/CHOKE position (Figure B)
- Start the generator manually with the Recoil (Pull) Start.
- Once the engine has started, GRADUALLY move the choke lever to the "RUN/OPEN" position until the engine levels off. Then let the engine run approximately 5 minutes BEFORE adding appliances or tools.
- You can now connect electrical devices.

GEN2000

2,000 Surge / 1,400 Running Watts

UNLEADED GASOLINE FUEL

GENERATOR SPECIFICATIONS:

- 3.5 HP Engine, 4 Stroke OHV
- Recoil Start
- 1.2 Gallon Fuel Tank
- Low Oil Shut Off
- UL Listed Electrical Components
- Engine Shut Off Switch
- Circuit Breaker & Power Outlets
- 1-12V DC Outlet
- 2 -120V AC Outlets
- Complies with EPA emissions
- Run time = 9 hours @ 50% load
- Decibel Rating < 68 db @ 0% load
- Warranty: 2 YEAR Limited Emissions
- Warranty: 1 YEAR Limited

OIL IS NOT INCLUDED WITH THIS GENERATOR. IT IS SOLD SEPARATELY.

Read and understand instruction manual before using generator.



On



Off


Fuel Petcock (Figure A)



Choke (Figure B)



Closed/Choke



Run/Open



TOLL-FREE NATIONWIDE HELP LINE! 866-460-9436

Need Help? Call Us First!

Monday-Friday 8:00-4:30 Central Time

Visit our website for Troubleshooting & Frequently Asked Questions

SPORTSMAN

www.sportsmanseriesbrand.com/generators