

WIREMOLD® NON-METALLIC RACEWAY FAQ:

What are the dimensions? The non-metallic raceway channel measures 7/16" by 1-15/16".

Can this be cut to size? Yes, the raceway channel can be cut to any length for a custom fit. A fine-tooth saw is recommended for the cleanest edges.

How does it attach to the wall? Because the raceway channel is meant for permanent power, the channel must be securely attached to the wall with screws into the studs or using wall anchors. Double-faced tape is not recommended.

Does it come with screws? No, mounting screws and anchors are sold separately in the accessory pack, item NMW910.

What kind of walls can this raceway be installed on? All of our raceways are designed to be installed with fasteners to the mounting surface. So as long as appropriate screws are used, this raceway can be installed on any interior wall including drywall, plaster, wood, brick, and concrete.

Can this be installed on the ceiling? Yes, raceway can be installed on the walls or ceilings.

Can I use this product on the floor to cover wires? No, this product is not designed to be installed on the floor and should only be installed on walls or ceilings.

Can this be used outdoors? No, this raceway is not rated for outdoor use. It should only be installed indoors in a dry location.

Can I use this with Romex? Yes, this raceway is rated for line voltage and can be used with Romex. However, it is designed for THHN or THWN type wiring, so the Romex may be fairly tight fit, especially around corners.

Can this be painted? Yes, non-metallic raceway can be painted. We recommend latex paint or an appropriate primer for plastics for the best paint adhesion.