

Follow This Step-By-Step Guide To Using Your Generator

1 Remove Generator From Package

2 Add Oil


Oil Type: SAE10W-30 Oil (Must add BEFORE first use)
Oil Capacity: 20.2 fluid oz
Because this generator includes Low Oil Shut Off, the generator will not start with low oil. Start out with 20.2 oz, then **fill until almost overflowing.**

3 Add Fuel

Unleaded gasoline only octane rating of 87 or higher
Maximum Capacity: 3.1 Gallon fuel tank

4 Start The Generator

- Use the generator **OUTDOORS** in a **WELL VENTILATED AREA**.
- **DO NOT CONNECT** electrical devices until **AFTER** the generator is started.
- Turn Power Switch to ON
- Turn **FUEL PETCOCK** to ON (Figure A)
- Adjust the **CHOKE** Lever Position to **CLOSED/START** (Figure B)
- Start the generator manually with the **Recoil** (Pull) Start.
- Once the engine has started, **GRADUALLY** move the choke lever to the "OPEN TO RUN" position until the engine levels off. Then let the engine run approximately 5 minutes **BEFORE** adding appliances or tools.
- You can now connect electrical devices.



Fuel Petcock (Figure A)



Choke (Figure B)



GEN3000IOF

3,000 Surge / 2,850 Running Watts

UNLEADED GASOLINE FUEL

GENERATOR SPECIFICATIONS:

- 2 - 120V A/C Outlets
- 1 - 120V RV Outlet
- 2 x USB Ports
- Recoil Start
- Parallel Port Output Capability (Parallel Cable Available Separately)
- Sine Wave Output For Sensitive Electronics
- 5.5 HP OHV Engine
- Displacement: 208cc
- Phase: Single
- AC Voltage: 120V @ 60Hz
- Decibel Rating <65 db @ 24 Feet
- Complies with EPA emissions
- Engine Run Time: 8 Hours @ 50% Load
- Fuel Tank Capacity: 3.1 Gallon
- High Altitude Use: This generator is not recommended for high altitude use above 3,000 feet.
- If you are using a generator at 3,000 feet above sea level, the generator may not function properly because of air flow getting through the carburetor.
- Warranty: 2 YEAR Limited Emissions
- Warranty: 1 YEAR Limited


OIL IS NOT INCLUDED WITH THIS GENERATOR. IT IS SOLD SEPARATELY.

Read and understand instruction manual before using generator.

GEN3000IOF

3,000 Surge / 2,850 Running Watts

UNLEADED GASOLINE FUEL



DO NOT CONNECT electrical devices until AFTER the generator is started.

WARNING

IF THERE IS ANY QUESTION ABOUT A CONDITION BEING SAFE OR UNSAFE, DO NOT OPERATE THIS PRODUCT!

Always follow Warning labels placed on the generator, and read and follow all Warning labels included inside the Product Manual.

WARNING: NEVER use a generator inside a home or a garage, EVEN IF the doors and windows are open.

ONLY USE OUTSIDE and far away from windows, doors and vents leading into an enclosed area.

Using a generator indoors can kill you in minutes. The generator produces an exhaust that contains carbon monoxide. This is a poison you cannot see or smell.

Do not attach a chain or rope to secure the generator to a post as this can be difficult to remove in the event of an emergency.

NOTES

Outlets available on this generator, from left to right:

- 2 x 120 Volt A/C Outlets
- 1 x 120 Volt RV Outlet

WARNING

IF THERE IS ANY QUESTION ABOUT A CONDITION BEING SAFE OR UNSAFE, DO NOT OPERATE THIS PRODUCT!

Always follow Warning labels placed on the generator, and read and follow all Warning labels included inside the Product Manual.

WARNING: NEVER use a generator inside a home or a garage, EVEN IF the doors and windows are open.

ONLY USE OUTSIDE and far way from windows, doors and vents leading into an enclosed area.

Using a generator indoors can kill you in minutes. The generator produces an exhaust that contains carbon monoxide. This is a poison you cannot see or smell.

Do not attach a chain or rope to secure the generator to a post as this can be difficult to remove in the event of an emergency.

TOLL-FREE NATIONWIDE HELP LINE! 866-460-9436

Need Help? Call Us First!

Monday-Friday 8:00-4:00 Central Time

Visit our website for Troubleshooting & Frequently Asked Questions

SPORTSMAN

www.sportsmanseriesbrand.com/generators

TOLL-FREE NATIONWIDE HELP LINE! 866-460-9436

Need Help? Call Us First!

Monday-Friday 8:00-4:00 Central Time

Visit our website for Troubleshooting & Frequently Asked Questions

SPORTSMAN

www.sportsmanseriesbrand.com/generators