


### II. RELATED TO INSTALLATION

#### 1. GENERAL

- To ensure the success of the installation, please read these instructions carefully before beginning.
- Before installation, prepare the required tools, such as Blade screwdriver, Adjustable wrench, Step ladder, Wire cutter.
- All electrical connections must be in accordance with the National Electrical Code. Qualified licensed electricians are required to conduct the installation of electrical wiring.
- The outlet box that is connected to the lighting must be directly supported by the building structure.
- Before starting the installation, disconnect the power to prevent electrical shock.
- NOTE: The important safeguards and installations appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution, and care are factors which can not be built into any product. There are factors that must be applied by the person(s) caring for and operating the fixture.

#### ii. CAUTION

- Rated 110-130V/60HZ, bulb 40W-60W maximum.
- Care should be taken to avoid damage to the surface of lighting and wire, wearing gloves are recommended when installing.
- Keep lighting away from acid, alkali and other corrosive chemical or gas, clean the lighting with clean soft cloth only.
- Installation must be carried out by qualified electrician only.
- Disconnect the power before installing, cleaning and replacing lighting.
- Never cover the lighting when power is connected.




### III. INSTRUCTIONS

1. Take up all the parts. The picture below shows the exact items that you receive in this product.

Please note that this picture may look different from the computer generate part table. The parts in the part table are not assembled but some parts in this part picture are assembled, so there may be fewer items in the picture than in the table.

#### 2. Part Table


Please note: The parts in this table are completely unassembled, for illustrative purpose. In the actual product that you receive, some parts are assembled and attached together.



### III. INSTRUCTIONS


1. Finish temp. installation according to below instructions.

#### RL4025GD



1


#### The steps hanging crystals



2

#### WIRE CONNECTION DIAGRAM

Wires meet safety standards are recommended to connect the supply circuit.



#### CANPY INSTALLATION INSTRUCTIONS

Please read all instructions carefully, before you proceed to install make sure that the power supply is turned off and remains off until installation is complete. Please not that each part has been assigned a letter. Please proceed in an alphabetical order.

#### FIXING INSTRUCTIONS

- Wire drawing lampshade (18) will be fixed on the Main body pipe (17) above, it fixed hornhood (16), and screw on the crystal ring (7).
- Take out screw (4) and rotate it into crystal lifting ring (7) (at least 6mm) and then lightened with washer (6) & hexagonal nut (6).
- Rotate the one nut of screw (4) till close to the first nut and then rotate screw (4) into batten (13). Make sure screw (4) should go through batten (13).
- Use outlet box screws (14) to fix batten (13) on outlet box (1).
- Take out ring cover (9) from crystal lifting ring (7) and then let the canopy (8) through crystal lifting ring (7). Adjust the crystal lifting ring to a certain height.
- Tighten the nut to fix on batten (13) in the right position.
- Ground Connection (See picture 1): there are one tapping hole & two dimples. Wind the supply ground wire (2) on the green ground screw (15) and then put it into tapping hole. Connect the fixture ground wire (3) with supply ground wire (2) by connecting terminal (12). Caution: DO NOT connect ground wire with supply power wire.
- Connect fixture supply wire (10) with power supply wire (11). Caution: Remember to distinguish the positive and negative charges. (See picture 2)
- Push canopy (8) up to the ceiling.
- Attach ring cover (9) on crystal lifting ring and fix canopy (8) as well.
- Put shade (18) on holder and lightened with out ring.
- Screw bulb in the holder.

