

September 19, 2017	HB1514L4 Triac/Phase-cut dimmers									
Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	minimum dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	3	3-Way only works with a 3-Way switch	7%
			TGCL-153P							
			Diva C.L			DVCL-153P				
			Skylark C.L			SCL-153P				
			Skylark Contour C.L			CTCL-153P				
		Lumea C.L	LGCL-153P							
		Maestro C.L	MACL-153M	Single-pole/3-way/ multi-location	150	Digital	2014	3	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	10%
			MSCL-VP153M	Single-pole/3-way/ multi-location	150	Digital/Vacancy Sensor	T2	3	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	10%
			MSCL-OP153M			Digital/Occupancy Sensor				
			MRF2-6CL	Single-pole/3-way/ multi-location	150	Digital and Wireless	M6	3	3-Way or multi-location only works with companion MA-R (not a dimmer)	10%
Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	6		10%		
Grafik T	GT-150	Single-pole/3-way/ multi-location	150	Digital	T6	3	3-Way or multi-location only works with companion GT-AD (not a dimmer)	9%		
RF C.L	Grafik T RF				GTJ 150			M6	8%	
Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless	SD11	3	Multi-location only works with Pico wireless remote PJ2	1%	
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	33%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	3	3-Way only works with a 3-Way switch	8%
		Sureslide	6672-1L	single	150	slide to off	NA	3		21%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	3	3-Way only works with a 3-Way switch	9%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	7	3-Way only works with remote RE00R Requires neutral wire connection	18%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	11	3-Way only works with remote DDOOR-DL Requires neutral wire connection	0%

