

February 12, 2018 **47XXN Triac/Phase-cut dimmers**

Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	minimum dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	18	3-Way only works with a 3-Way switch	1%
			TGCL-153P							
		Diva C.L	DVCL-153P							
		Skylark C.L	SCL-153P							
		Skylark Contour C.L	CTCL-153P							
		Lumea C.L	LGCL-153P							
		Maestro C.L	MACL-153M	Single-pole/3-way/multi-location	150	Digital	2014	18	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	1%
			MSCL-VP153M	Single-pole/3-way/multi-location	150	Digital/Vacancy Sensor	T2	18	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	2%
			MSCL-OP153M	Single-pole/3-way/multi-location		Digital/Occupancy Sensor				
			MRF2-6CL	Single-pole/3-way/multi-location	150	Digital and Wireless	M6	18	3-Way or multi-location only works with companion MA-R (not a dimmer)	2%
	Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	30		1%	
	Grafik T	GT-150	Single-pole/3-way/multi-location	150	Digital	T6	18	3-Way or multi-location only works with companion GT-AD (not a dimmer)	1%	
RF C.L	Grafik T RF	GTJ 150	M6			1%				
	Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless	SD11	18	Multi-location only works with Pico wireless remote PJ2	0%
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	37	3-Way only works with a 3-Way switch	20%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	18	3-Way only works with a 3-Way switch	1%
		Sureslide	6672-1L	single	150	slide to off	NA	18		3%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	18	3-Way only works with a 3-Way switch	2%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	37	3-Way only works with remote RE00R Requires neutral wire connection	12%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	55	3-Way only works with remote DDOOR-DL Requires neutral wire connection	9%

