

# Pendant Light Assembly & Installation Guide

## 1. Tools Required

- Screwdriver (Flathead and Phillips)
- Wire Strippers
- Electrical Tape
- Ladder
- Voltage Tester
- Drill (if needed)

## 2. Safety Precautions

**Always turn off the power at the circuit breaker before installation.**

- Use a voltage tester to confirm the power is off.
- Consult a licensed electrician if unsure about any step.
- Make sure the ceiling box can support the weight of the fixture.

## 3. Installation Steps

**Important: Match wire colors correctly and secure with wire nuts.**

1. Remove any existing fixture.
2. Attach the mounting bracket to the ceiling box.
3. Connect the ground wire (green/bare) to the box ground screw or wire.
4. Connect black to black (hot), and white to white (neutral).
5. Secure all connections with electrical tape.
6. Carefully tuck wires into the ceiling box.
7. Mount the canopy to the bracket and adjust pendant height.
8. Install the bulb(s) and restore power to test the light.

## 4. Bulb and Wattage Information

# Pendant Light Assembly & Installation Guide

**Use only the bulb type and wattage specified by the manufacturer.**

Most pendant lights use E26 base bulbs with a maximum wattage of 60W per socket. Check the label on the fixture.

## 5. Maintenance Tips

**Turn off the power before cleaning or performing maintenance.**

- Wipe the fixture with a soft, dry cloth.
- Avoid harsh chemicals or abrasive materials.
- Replace bulbs as needed.
- Periodically inspect mounting and wiring for safety.