8 Ft. 40W (75W Replacement) Daylight (5000K) FA8 Base T12 Direct Replacement (Type A) LED Linear Tube (2-Pack)

Features

- Works with most magnetic or electronic ballasts so no rewiring or electrician is required
- Plug and play Type A installation lowers labor costs when converting T12 fixtures to LED
- Uses up to 45% less energy than a 75W fluorescent tube, cutting utility costs fixture by fixture



Specifications

Item Number	Item Length (In)	Item Width (In)	Bulb Shape
T1296/850/A/LEDG2/2	93.8	1.6	T12
Bulb Base	**Brightness (LUMENS)**	**Color Accuracy (CRI)**	**Color Temperature (CCT)**
FA8	5000	80	5000
Life Hours	**Life Years**	**Voltage (V)**	**Replacement (Wattage)**
35000	32.0	120-277	75
Energy Used (Wattage)	**Battery Operated**	**Pack Quantity**	**Smart**
40	No	2	No
Portable	**Dimmable**	**Enclosed Fixture Rated**	**Safety Location**
No	No	No	Damp
CEC Compliant			
Not Regulated			