

XP8500EH

DUAL FUEL PORTABLE GENERATOR
8,500 STARTING WATTS • 7,000 RUNNING WATTS






XP8500EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS




X4
120V 20A
GFCI Outlet



X1
12V
Automotive
Outlet



X1
120/240V
30A Twist
Lock



X2
2.1A & 1A
USB Outlets

SPECS

Watts (Gasoline)	8,500 (peak) • 7,000 (running)
Watts (Propane)	8,075 (peak) • 6,650 (running)
Engine	OHV 420cc
Amperage	58.33A / 29.17A
Voltage	120V / 240VAC & 12VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	11.5 hrs
Runtime (Propane) at 50% Load	8 hrs