



Battery clamp-O ring bare end 10AWG, 3.3ft 12V Car Plug-O ring bare end 16AWG, 3.3ft

Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Microwave Ovens, Computers, Power Tools and More
- Comes With Battery Clamps Cable.
- USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 400 Watt Continuous Output, 800 Watts Surge
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power: 400W (Continuous), 800W(Peak)

Voltage / Current: 120 Vac / 12.5A

Frequency: 60Hz

Waveform: Pure Sinewave

AC Outlet: 2 x 3Prong GFCI AC outlet

DC OUTPUT

USB: 1 x 5V/2.1A

DC INPUT

Voltage (nominal): 12Vdc

Operation Range: 10.5-15.5Vdc / 38A

Material: ABS, Stel, Aluminum

PROTECTION:

Input Undervoltage Warning: 11.0Vdc

Input Undervoltage Shutdown: 10.5Vdc

Input Undervoltage Recovery: 12.0Vdc

Input Overvoltage Shutdown: 15.75Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 38304

UPC Code: 839290003084

Country of Origin: China / Hong Kong

Product Dimensions: 7.8 x 7 x 3.3 in

Color box Dimensions: 10.88 x 8.91 x 5.75 in

Product Weight: 5.2 lbs with package

4.4 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

