

1005 975 902
MATTE BLACK
NEGRO MATE

5 in Modern Canopy Kit


Kit de cubierta moderna 12.7cm

Use modern canopy kits to update or enhance décor. Can also be used to replace worn or broken parts.

Kit Includes: 1 Canopy (E), 1 Crossbar (F), 4 Mounting Screws (C & D), 1 Lock Washer (B), 1 Lock Nut (B), 1 Screw Collar Loop (A), 2 Cap Nuts

INSTRUCTIONS:

1. Turn off power supply. Install and use this product according to your local electrical codes and regulations.
2. If the lighting fixture is mounted to a ceiling outlet box, the box must be supported directly by the building structure and be capable of supporting up to 50 lbs.
3. Attach the threaded loop (A) to the canopy (E) using the nut and lock washer (B) provided. Tighten.
4. Thread both 1.2 in screws (C) into the threaded holes from the offset side of the crossbar (F).
5. Mount the crossbar to the ceiling box using both 1/2 in screws (D). Tighten until the bracket is flush with the ceiling.
6. Pass fixture wires through hold in loop to the back of canopy.
7. While supporting the fixture, connect fixture wires to current supply wires in ceiling outlet box. Use wire connectors following manufacturer's directions.
8. While supporting the fixture at the canopy, attach the canopy to the ceiling box using the cap nuts . Tighten securely. Be sure the fixture wires are carefully placed inside the ceiling outlet box.




Usar kits de cubierta moderna para modernizar o mejorar la decoración. También pueden usarse para reponer partes o piezas rotas o desgastadas.

El kit incluye: 1 cubierta (E), 1 barra transversal (F), 4 tornillos de montaje (C y D), 1 arandela de seguridad (B), 1 contratuerca (B), 1 bucle de collarín con tornillo (A), 2 tuercas para tapa

INSTRUCCIONES:

1. Cortar el suministro de electricidad. Instalar y usar este producto cumpliendo con las regulaciones y códigos eléctricos de tu localidad.
2. Si la lámpara se monta a una caja eléctrica en el cielo raso, esta tiene que quedar fijada directamente a la estructura de la edificación y ser capaz de soportar hasta 22.3 kg.
3. Fijar el lazo con rosca (A) a la cubierta (E) con la tuerca y arandela de seguridad (B) incluidas. Apretar.
4. Enroscar ambos tornillos de 3.05 cm (C) en los orificios con rosca del lado desplazado de la barra transversal (F).
5. Montar la barra transversal en la caja del cielo raso con ambos tornillos de 1.27 cm (D). Apretar hasta que el soporte quede al ras con el cielo raso.
6. Pasar los cables de la lámpara, a través del soporte en el bucle, a la parte posterior de la cubierta.
7. Al sostener la lámpara, conectarla a los cables de suministro de corriente en la caja eléctrica del cielo raso. Usar los conectores de cable siguiendo las instrucciones del fabricante.
8. Sosteniendo la lámpara en la cubierta, fijarla a la caja del cielo raso usando las tuercas de la tapa . Apretar firmemente. Asegurar que los cables de la lámpara están cuidadosamente colocados dentro de la caja eléctrica en el cielo raso.




FOR ASSISTANCE, CALL:
SI NECESITA AYUDA, LLAME AL:
1-877-527-0313
HOMEDEPOT.COM

MODEL/MODELO 804774

MADE IN VIETNAM
HECHO EN VIETNAM

DISTRIBUTED BY:
DISTRIBUIDO POR:
HOME DEPOT
2455 PACES FERRY RD.
ATLANTA, GA 30339



DATE	11.09.20	ROUND	3	
A DIVISION OF				
PART	804774			
UPC #:	8 87480 04774 5			
SKU #:	1005 975 902			
DESIGNER:	MP			
BRAND:	Commercial Electric			
DESC.:	Lamp Accessories			
PACKAGE TYPE:	Card			
	5.7874" w x 8.6614" h			
	PRINTED COLORS			

Country of Origin: XXXXXX
Helvetica Condensed
7pt

 Vendor is responsible for updating the Country of Origin

Vendor ID: XXXXXX
Helvetica Condensed
5pt

 Vendor is responsible for updating the vendor id#