



# XP15000E

## PORTABLE GAS GENERATOR

15,000 STARTING WATTS • 12,000 RUNNING WATTS





# XP15000E

PORTABLE GAS GENERATOR

## FEATURES



## OUTLETS



**X4**  
120V 20A  
GFCI Outlet



**X1**  
120V 30A  
Twist Lock



**X1**  
120/240V  
30A Twist  
Lock



**X1**  
120/240V  
50A Heavy  
Duty Outlet

## SPECS

<b>Watts</b>	15,000 (peak) • 12,000 (running)
<b>Engine</b>	V-Twin 713cc
<b>Amperage</b>	100.00A / 50.00A
<b>Voltage</b>	120V / 240VAC
<b>Frequency</b>	60 Hz
<b>Fuel Type</b>	Gasoline
<b>Runtime at 50% Load</b>	8.83 hrs
<b>Start Type</b>	Electric