

POWERING YOUR *life.*

Model 201192

UPC 817198026015

Warranty 5 Years

30 AMP

Features



POWERS HARD-WIRED CIRCUITS
no need for extension cords



Pre-wired for **QUICK AND EASY INSTALLATION**



PUSH-BUTTON change between utility and generator power



POWER SOURCE INDICATING LIGHTS
utility and generator

Accessories



POWER CORD



POWER INLET BOX



Specifications

AMPERAGE (A)	30
VOLTAGE (V)	240
ENCLOSURE RATING	NEMA 1 (Indoor)
CIRCUITS	8
BREAKERS INCLUDED	1-30A 2-pole 1-20A 1-pole 5-15A 1-pole
COMPLIANCE	UL 1008 / CSA C22.2 No. 178.1

Champion's 30-Amp manual transfer switch is prewired and has 8 circuits, so you no longer need extension cords to get power from your generator into your home. The switch allows you to easily change between utility and generator power, while the LED lights indicate active power sources: utility, generator, or both.

Inside the box

INSTALLATION MANUAL
PRE-WIRED MANUAL TRANSFER SWITCH

25 FT. (7.6 M) POWER CORD
POWER INLET BOX

What You Need

50A 2-POLE CIRCUIT BREAKER
NM-B ELECTRICAL WIRE
ELECTRICAL CONDUIT

CONDUIT FITTINGS
WIRE CONNECTIONS

*Specifications, descriptions and illustrations are subject to change without notice.



PACKAGE (gross)
Weight: 40.1 lb.
Size: 19.6 x 18.8 x 11.6 in.



PRODUCT (net)
Weight: 33.1 lb.
Size: 17.6 x 15.3 x 4.4 in.

CHAMPION POWER EQUIPMENT, INC.
12039 Smith Ave., Santa Fe Springs, CA 90670, USA
www.championpowerequipment.com