



POWERING YOUR *life.*

# Model 201120

UPC 817198025728

Warranty 3 Years

## 4650

**STARTING WATTS**  
Propane: 4650

## 3650

**RUNNING WATTS**  
Propane: 3285



**RUN TIME**  
14 hrs.



**RUN TIME**  
21 hrs.



**NOISE LEVEL**  
61 dBA



### ELECTRIC START

Push button start includes **BATTERY**



### ULTRA QUIET

**LOW NOISE** – high performance



### EZ START DIAL

Confusion free **ENGINE START-UP**



### INTELLI GAUGE

**5-MODE** display with power meter



### PARALLEL READY

Link 2 units for **DOUBLE POWER**



Receptacles



**12V DC**  
Automotive



**20 AMP**  
120V, 5-20R



**30 AMP RV**  
120V, TT-30R



**Parallel**

### Specifications

<b>START TYPE</b>	Electric, Recoil
<b>VOLTAGE (V) AC</b>	120
<b>VOLTMETER</b>	Intelligauge w/ Power Meter
<b>ENGINE SIZE (cc)</b>	212
<b>FUEL TYPE</b>	Gasoline or Propane
<b>GASOLINE CAPACITY (gal.)</b>	2.3
<b>OIL TYPE</b>	10W-30
<b>OIL CAPACITY (fl. oz./mL)</b>	16.9/500
<b>LOW OIL SHUT-OFF</b>	Yes
<b>EMISSIONS</b>	EPA III/CARB



## SHIELD

**CARBON MONOXIDE  
AUTO-SHUTOFF SYSTEM**



**OIL INCLUDED**



Our 4650-watt inverter generator meets ANSI/PGMA G300-2018 requirements and features CO Shield, the Carbon Monoxide auto shutoff system. The 212cc engine runs for up to 14 hours on gasoline or up to 21 hours with a 20-lb propane tank plus you can increase your power with the optional Parallel Kit.



### Inside the box

<b>GENERATOR</b>	<b>PROPANE HOSE 6 FT.</b>	<b>REVERSIBLE PHILLIPS/ FLATHEAD SCREW- DRIVER</b>
<b>OPERATOR'S MANUAL</b>	<b>USB ADAPTER</b>	
<b>OIL FUNNEL</b>	<b>8/10 MM WRENCH</b>	
<b>ENGINE OIL</b>	<b>SPARK PLUG SOCKET</b>	



### What You Need

**GASOLINE OR PROPANE**

\*Specifications, descriptions and illustrations are subject to change without notice.



**PACKAGE (gross)**  
Weight: 117 lb.  
Size: 27.8 x 20.9 x 23.4 in.



**PRODUCT (net)**  
Weight: 103 lb.  
Size: 23.2 x 17.7 x 20.1 in.

**CHAMPION POWER EQUIPMENT, INC.**  
12039 Smith Ave., Santa Fe Springs, CA 90670, USA  
www.championpowerequipment.com