

Product data sheet

Characteristics

QO132M100PCVP

Load center, QO, 1 phase, 32 spaces, 32 circuits, 100A convertible main breaker, PoN, NEMA1, combo cover, UL, value pack



Main

Marketing Trade Name	QO
Product Type	Load Center value pack
Cover Type	Combination flush/surface cover
Provided Equipment	Cover

Complementary

Tightening Torque	Cover 20 lb.in
Load Center Type	Main breaker
Rated Current	100 A
Number of Spaces	32
Max Short Circuit Current Rating	22 kA
Maximum Number of Single Pole Circuits	32
Maximum Number of Tandem Breakers	6
Number of Phases	1 phase
Ground Bar	Grounding bar (ordered separately)
Box Number	8
Height	26.04 in (661.42 mm)
Width	14.25 in (361.95 mm)
Depth	3.75 in (95.25 mm)

Environment

Enclosure Rating	NEMA 1 indoor
Ambient Air Temperature for Operation	23 °F (-5 °C) 104 °F (40 °C)
Product Certifications	UL Listed

Ordering and shipping details

Category	00184 - MISC. QO 1PH LOAD CENTERS
Discount Schedule	DE3A
GTIN	00785901085904
Nbr. of units in pkg.	1
Package weight(Lbs)	27.81 lb(US) (12.61 kg)
Returnability	Yes
Country of origin	US

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Offer Sustainability

REACH Regulation	REACH Declaration
REACH free of SVHC	Yes
EU RoHS Directive	Compliant EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	China RoHS Declaration