



XP12000E

PORTABLE GAS GENERATOR

12,000 STARTING WATTS • 9,500 RUNNING WATTS





XP12000E

PORTABLE GAS GENERATOR

FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- No-Flat Tires
- All-Copper Windings
- Fully-Loaded Power Panel
- Low Oil Shutoff
- Idle Control



DOUBLE THE 120V POWER

OUTLETS



X2
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

| | |
|----------------------------|---------------------------------|
| Watts | 12,000 (peak) • 9,500 (running) |
| Engine | OHV 457cc |
| Amperage | 79.17A / 39.58A |
| Voltage | 120V / 240VAC & 12VDC |
| Frequency | 60 Hz |
| Fuel Type | Gasoline |
| Runtime at 50% Load | 8.83 hrs |
| Start Type | Electric / Recoil |